

# ELECTRO CLEANER

SOLVENTS AND DEGREASERS

- **Powerful jet spray**
- **High resolution**
- **Leaves no residue**
- **Non-conductive, non-corrosive**

## PRODUCT DESCRIPTION :

High quality spray for cleaning electrical contacts.

## APPLICATIONS :

- Switches
- Batteries
- Contact points
- Mixing panels
- Contact boxes

## INSTRUCTIONS :

Bring the Aerosol to room temperature.

Ideal processing temperature is 5 to 30°C.

Shake before use.

For treating, turn off electrical installations. Inject the parts to be treated until the contamination has disappeared. Collect contaminated contact cleaner and treat as chemical waste.

After evaporation of the solvent (at least 15 minutes), switch the electrical installations on.

## SPECIFICATIONS:

<b>Content:</b>	400 ml
<b>Base:</b>	Aliphatic Hydrocarbons with alcohol
<b>Propellant:</b>	Carbon dioxide
<b>VOC-content:</b>	Approx. 97% w/w
<b>Colour:</b>	Transparent
<b>Odour:</b>	Characteristic
<b>Density at 20°C:</b>	0,73 gr/ml
<b>Yield:</b>	3,8 gr/sec.
<b>Refractive index at 20°C:</b>	1,370

